

October 2007

# **DF005S - DF10S Bridge Rectifiers**

# **Features**

- Surge overload rating: 50 amperes peak.
- · Glass passivated junction.
- · Low leakage.
- UL certified, UL #E96005.



# Absolute Maximum Ratings \* Ta = 25°C unless otherwise noted

Symbol	Parameter	Value					l luite		
		005S	01S	02S	04S	06S	08S	10S	Units
$V_{RRM}$	Maximum Repetitive Reverse Voltage	50	100	200	400	600	800	1000	V
$V_{RMS}$	Maximum RMS Bridge Input Voltage	35	70	140	280	420	560	700	V
$V_R$	DC Reverse Voltage (Rated V <sub>R</sub> )	50	100	200	400	600	800	1000	V
I <sub>F(AV)</sub>	Average Recitified Forward Current  @ T <sub>A</sub> = 40°C				1.5				Α
I <sub>FSM</sub>	Non-Repetitive Peak Forward Surge Current 8.3ms Single Half-Sine-Wave		50			А			
T <sub>STG</sub>	Storage Temperature Range		-55 to +150			°C			
T <sub>J</sub>	Operating Junction Temperature	-55 to +150			°C				

<sup>\*</sup> These ratings are limiting values above which the serviceability of any semiconductor device may by impaired.

# **Thermal Characteristics**

Symbol	Parameter	Value	Units	
$P_D$	Power Dissipation	3.1	W	
$R_{\theta JA}$	Thermal Resistance, Junction to Ambient, * per leg	40	°C/W	

<sup>\*</sup> Device mounted on PCB with 0.5  $\times$  0.5" (13  $\times$  13mm).

# Electrical Characteristics T<sub>C</sub> = 25°C unless otherwise noted

Symbol	Parameter	Value	Units
V <sub>F</sub>	Forward Voltage, per element @ 1.0A	1.1	V
I <sub>R</sub>	Reverse Current, per element @ Rated $V_R$ $T_A = 25$ °C $T_A = 125$ °C	50 500	μΑ μΑ
	I <sup>2</sup> t Rating for Fusing t < 8.35ms	10	A <sup>2</sup> s
C <sub>T</sub>	Total Capacitance, per leg V <sub>R</sub> = 4.0v, f = 1.0MHz	25	pF

1

# **Typical Performance Characteristics**

Figure 1.




Figure 2.




Figure 3.





Figure 4.







#### **TRADEMARKS**

The following are registered and unregistered trademarks and service marks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

ACEx<sup>®</sup>
Build it Now<sup>™</sup>
CorePLUS<sup>™</sup>
CROSSVOLT<sup>™</sup>
CTL<sup>™</sup>

Current Transfer Logic™ EcoSPARK®

Fairchild<sup>®</sup>
Fairchild Se

Fairchild Semiconductor® FACT Quiet Series™ FACT®

FACT®
FAST®
FastvCore™
FPS™
FRFET®

Global Power Resource<sup>SM</sup>

Green FPS™
Green FPS™ e-Series™
GTO™

i-Lo™ IntelliMAX™ ISOPLANAR™ MegaBuck™ MICROCOUPLER™

MicroFET<sup>TM</sup>
MicroPak<sup>TM</sup>
Motion-SPM<sup>TM</sup>
OPTOLOGIC<sup>®</sup>
OPTOPLANAR<sup>®</sup>

PDP-SPM™ Power220® Power247<sup>®</sup>
POWEREDGE<sup>®</sup>
Power-SPM<sup>TM</sup>
PowerTrench<sup>®</sup>

Programmable Active Droop™

QFET<sup>®</sup> QS™

QT Optoelectronics<sup>™</sup> Quiet Series<sup>™</sup> RapidConfigure<sup>™</sup> SMART START<sup>™</sup> SPM<sup>®</sup>

STEALTH™
SuperFET™
SuperSOT™-3
SuperSOT™-6

SuperSOT™-8 SyncFET™

The Power Franchise®

the wer franchise
TinyBoost™
TinyBuck™
TinyBuck™
TinyBuck™

TinyLogic®
TINYOPTO™
TinyPower™
TinyPWM™
TinyWire™
µSerDes™
UHC®
UniFET™
VCX™

#### DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

## LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

### As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.
- A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

## PRODUCT STATUS DEFINITIONS

#### **Definition of Terms**

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.

Rev. I30